

## Programming Example: List connected VISA compatible resources using PyVISA

February 19, 2019

PyVISA is a software library that enables Python applications to communicate with resources (typically instruments) connected to a controlling computer using different buses, including: GPIB, RS-232, LAN, and USB.

This example scans and lists the available resources.

It requires PyVISA to be installed (see the PyVISA documentation for more information)

\*\*\*

```
#Example that scans a computer for connected instruments that
#are compatible with the VISA communication protocol.
#
#The instrument VISA resource ID for each compatible instrument
#is then listed.
#
#
#Dependencies:
#Python 3.4 32 bit
#PyVisa 1.7
#
#Rev 1: 08302018 JC
```

```
import visa
```

```
def main():
```

```
    rm = visa.ResourceManager()
    print (rm.list_resources())
```

```
if __name__ == '__main__':
```

```
    main()
```

\*\*\*\*\*

Here is the code:

```
PyVisaResourceList.py - C:/Users/jayre/Documents/Application Notes/PyVISA/PyVisaResourceList.py (3.4.3)
File Edit Format Run Options Window Help
#Example that scans a computer for connected instruments that
#are compatible with the VISA communication protocol.
#
#The instrument VISA resource ID for each compatible instrument
#is then listed.
#
#
#Dependencies:
#Python 3.4 32 bit
#PyVisa 1.7
#
#Rev 1: 08302018 JC

import visa

def main():
    rm = visa.ResourceManager()
    print (rm.list_resources())

if __name__ == '__main__':
    main()
|
```

And here is the result of a scan:

```
Python 3.4.3 Shell
File Edit Shell Debug Options Window Help
Python 3.4.3 (v3.4.3:9b73f1c3e601, Feb 24 2015, 22:43:06) [MSC v.1600 32 bit (Intel)] on win32
Type "copyright", "credits" or "license()" for more information.
>>> ===== RESTART =====
>>>
('USB0::0x0483::0x7540::SPD3XGB4150080::INSTR', 'USB0::0xF4EC::0x1301::SVA1XEAX2
R0073::INSTR', 'TCPIP0::192.168.55.122::inst0::INSTR')
>>> |
```

Each connected instrument returns a specific formatted string of characters called the VISA Resource ID.

The resource ID format is as follows:

'Communication/Board Type (USB, GPIB, etc.):Resource Information (Vendor ID, Product ID, Serial Number, IP address, etc.):Resource Type'

In the response, each resource is separated by a comma. So, we have three resources listed in this example:

'USB0::0x0483::0x7540::SPD3XGB4150080::INSTR' - This is a power supply (SPD3X) connected via USB (USB0)

'USB0::0xF4EC::0x1301::SVA1XEAX2R0073::INSTR' - This is a vector network analyzer (SVA1X) connected via USB (USB0)

'TCPIP0::192.168.55.122::inst0::INSTR' - This is an instrument connected via LAN using a TCPIP connection at IP address 192.168.55.122



### **North American Headquarters**

SIGLENT Technologies America, Inc  
6557 Cochran Rd Solon, Ohio 44139  
Tel: 440-398-5800  
Toll Free: 877-515-5551  
Fax: 440-399-1211  
[info@siglent.com](mailto:info@siglent.com)  
[www.siglentamerica.com/](http://www.siglentamerica.com/)

### **European Sales Offices**

SIGLENT TECHNOLOGIES EUROPE GmbH  
Staetzlinger Str. 70  
86165 Augsburg, Germany  
Tel: +49(0)-821-666 0 111 0  
Fax: +49(0)-821-666 0 111 22  
[info-eu@siglent.com](mailto:info-eu@siglent.com)  
[www.siglenteu.com](http://www.siglenteu.com)

### **Asian Headquarters**

SIGLENT TECHNOLOGIES CO., LTD.  
Blog No.4 & No.5, Antongda Industrial Zone,  
3rd Liuxian Road, Bao'an District,  
Shenzhen, 518101, China.  
Tel: + 86 755 3661 5186  
Fax: + 86 755 3359 1582  
[sales@siglent.com](mailto:sales@siglent.com)  
[www.siglent.com/ens](http://www.siglent.com/ens)